

| (()) ELATEC RFID | | TWN3 | | | | | | |
|---------------------------------|---------------------------|----------------------------|------------|-----------|---------|----------|----------|--|
| with Antenna → | MIFARE | MIFARE NFC, Mini Reader | Multi ISO | Legic NFC | Inditag | HID Prox | Multi125 | |
| without Antenna → | Nano Modul | | Nano Modul | | | | | |
| 13.56 MHz | ISO14443A | | | | | | | |
| | MIFARE Classic | ✓ | ✓ | ✓ | ✓ 2) | | | |
| | MIFARE Classic EV1 | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 2) | | | |
| | MIFARE Mini | ✓ | ✓ | ✓ | ✓ 1) | | | |
| | MIFARE DESFireEV1 | ✓ 1) | ✓ 12) | ✓ | ✓ 2) | | | |
| | MIFARE Plus S,X | ✓ 10) | ✓ | ✓ | ✓ 2) | | | |
| | MIFARE Pro X | ✓ 1) | ✓ | ✓ | ✓ 2) | | | |
| | MIFARE Smart MX | ✓ 1) | ✓ | ✓ | ✓ 2) | | | |
| | MIFARE Ultralight | ✓ | ✓ | ✓ | ✓ 2) | | | |
| | MIFARE Ultralight C | ✓ 11) | ✓ | ✓ | ✓ 2) | | | |
| | MIFARE Ultralight EV1 | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 2) | | | |
| | SLE44R35 | ✓ | ✓ | ✓ | ✓ 1) | | | |
| | SLE66Rxx (my-d move) | ✓ | ✓ | ✓ | ✓ 2) | | | |
| | LEGIC Prime | | | | ✓ | | | |
| | LEGIC Advant | ✓ 1) | ✓ 1) | ✓ 1) | ✓ | | | |
| | NTAG2xx | ✓ | ✓ | ✓ | ✓ 2) | | | |
| | PayPass | ✓ 11) | ✓ 2) | ✓ 2) | ✓ 1) | | | |
| | ISO14443B | | | | | | | |
| | Calypso | | ✓ 2) | ✓ 2) | | | | |
| | CEPAS | | ✓ 2) | ✓ 2) | | | | |
| | Moneo | | ✓ 2) | ✓ 2) | | | | |
| | Pico Pass | | ✓ 2) | ✓ 2) | ✓ 1) | | | |
| | SR1512, SRT512 | | ✓ | ✓ | | | | |
| | SR14K, SRIX4K | | ✓ | ✓ | | | | |
| | ISO18092/ECMA-340 | | | | | | | |
| | Sony FeliCa | | ✓ 1) | ✓ 1) | ✓ 1) | | | |
| | NFC Forum Tag 1-4 | | ✓ | ✓ | ✓ 2),3) | | | |
| | NFC Peer-to-Peer | | | | | | | |
| | ISO15693 | | | | | | | |
| | EM4x33 | | | ✓ | | | | |
| | EM4x35 | | | ✓ | ✓ 2) | | | |
| | HID iCLASS | | | ✓ 1) | ✓ 1) | | | |
| | HID iCLASS SE/SR | | | ✓ 1) | ✓ 1) | | | |
| | ICODE SLI | | | ✓ | ✓ 2) | | | |
| | M24LR16/64 | | | ✓ | | | | |
| | MB89R118/119 | | | ✓ | | | | |
| | Tag-it | | | ✓ | ✓ 2) | | | |
| | SRF55Vxx (my-d vcinity) | | | ✓ 2) | ✓ 2) | | | |
| | 125 kHz / 134.2kHz | AWID | | | | | | |
| | | ioProx | | | | | | |
| CASI-RUSCO | | | | | | | | |
| Cotag | | | | | | | | |
| EM4100,4102, 4200 ⁶⁾ | | | | | | | ✓ | |
| EM4050, 4150, 4450, 4550 | | | | | | | ✓ | |
| EM4305 | | | | | | | | |
| FDX-B | | | | | | | ✓ | |
| G-Prox | | | | | | | | |
| HID DuoProx II (1336) | | | | | | ✓ | | |
| HID ISO Prox II (1386) | | | | | | ✓ | | |
| HID Micro Prox (1391) | | | | | | ✓ | | |
| HID ProxKey III (1346) | | | | | | ✓ | | |
| HID Prox | | | | | | ✓ | | |
| HID Prox II (1326) | | | | | | ✓ | | |
| HITAG 1,2, S | | | | | | | ✓ 11) | |
| Indala | | | | | ✓ | | | |
| Keri | | | | | | | | |
| Miro | | | | | | | ✓ | |
| Nexwatch | | | | | | | | |
| Pyramid | | | | | | | | |
| Q5 | | | | | | | ✓ 5) | |
| T5557, T5567, T5577 | | | | | | ✓ 5) | | |
| TIRIS/HDX | | | | | | | | |
| TITAN (EM4050) | | | | | | ✓ | | |
| UNIQUE | | | | | | ✓ | | |
| ZODIAC | | | | | | ✓ | | |

| (()) ELATEC RFID | | TWN4 | | | | | | |
|------------------------|---------------------------|---------------------------------|----------------|----------------|----------------|-----------------|-------------------|------|
| with Antenna → | | MultiTech HF Mini Reader | MultiTech | MultiTech P | MultiTech PI | MultiTech LEGIC | MultiTech LEGIC P | |
| without Antenna → | | | MultiTech Core | MultiTech Core | MultiTech Core | MultiTech Core | MultiTech Core | |
| 13.56 MHz | ISO14443A | | | | | | | |
| | MIFARE Classic | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | MIFARE Classic EV1 | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | |
| | MIFARE Mini | ✓ | ✓ | ✓ | ✓ | ✓ 2) | ✓ 2) | |
| | MIFARE DESFireEV1 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | MIFARE Plus S,X | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | MIFARE Pro X | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | |
| | MIFARE Smart MX | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | |
| | MIFARE Ultralight | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | MIFARE Ultralight C | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | MIFARE Ultralight EV1 | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | |
| | SLE44R35 | ✓ | ✓ | ✓ | ✓ | ✓ 2) | ✓ 2) | |
| | SLE66Rxx (my-d move) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | LEGIC Prime | | | | | ✓ | ✓ | |
| | LEGIC Advant | ✓ 1) | ✓ 1) | ✓ 1) | ✓ 1) | ✓ | ✓ | |
| | NTAG2xx | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | ✓ 7) | |
| | PayPass | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | |
| | ISO14443B | | | | | | | |
| | Calypso | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 2) | ✓ 2) | |
| | CEPAS | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 2) | ✓ 2) | |
| | Moneo | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 2) | ✓ 2) | |
| | Pico Pass | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | |
| | SRI512, SRT512 | ✓ | ✓ | ✓ | ✓ | ✓ 2) | ✓ 2) | |
| | SRI4K, SRIX4K | ✓ | ✓ | ✓ | ✓ | | | |
| | ISO18092/ECMA-340 | | | | | | | |
| | Sony FeliCa | ✓ 9) | ✓ 9) | ✓ 9) | ✓ 9) | ✓ 9) | ✓ 9) | |
| | NFC Forum Tag 1-4 | ✓ | ✓ | ✓ | ✓ | ✓ 3) | ✓ 3) | |
| | NFC Peer-to-Peer | ✓ | ✓ | ✓ | ✓ | | | |
| | ISO15693 | | | | | | | |
| | EM4x33 | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | | | |
| | EM4x35 | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | |
| | HID iCLASS | ✓ 1) | ✓ 1) | ✓ 1) | ✓ 14) | ✓ 1) | ✓ 1) | |
| | HID iCLASS SE/SR | ✓ 1) | ✓ 1) | ✓ 1) | ✓ 14) | ✓ 1) | ✓ 1) | |
| | ICODE SLI | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | M24LR16/64 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | MB89R118/119 | | | | | | | |
| | Tag-it | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| | SRF55Vxx (my-d vcinity) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | ✓ 8) | |
| | 125 kHz / 134.2kHz | AWID | | ✓ | ✓ | ✓ | ✓ | ✓ |
| | | ioProx | | | ✓ | ✓ | | ✓ |
| | | CASI-RUSCO | | ✓ | ✓ | ✓ | ✓ | ✓ |
| | | Cotag | | | ✓ | ✓ | | ✓ |
| | | EM4100,4102, 4200 ⁶⁾ | | ✓ | ✓ | ✓ | ✓ | ✓ |
| | | EM4050, 4150, 4450, 4550 | | ✓ | ✓ | ✓ | ✓ | ✓ |
| | | EM4305 | | ✓ 4) | ✓ 4) | ✓ 4) | ✓ 4) | ✓ 4) |
| FDX-B | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| G-Prox | | | | ✓ 13) | ✓ 13) | | ✓ 13) | |
| HID DuoProx II (1336) | | | | ✓ | ✓ | | ✓ | |
| HID ISO Prox II (1386) | | | | ✓ | ✓ | | ✓ | |
| HID Micro Prox (1391) | | | | ✓ | ✓ | | ✓ | |
| HID ProxKey III (1346) | | | | ✓ | ✓ | | ✓ | |
| HID Prox | | | | ✓ | ✓ | | ✓ | |
| HID Prox II (1326) | | | | ✓ | ✓ | | ✓ | |
| HITAG 1,2, S | | | ✓ 11) | ✓ 11) | ✓ 11) | ✓ 11) | ✓ 11) | |
| Indala | | | | ✓ | ✓ | | ✓ | |
| Keri | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Miro | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Nexwatch | | | | ✓ | ✓ | | ✓ | |
| Pyramid | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Q5 | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| T5557, T5567, T5577 | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| TIRIS/HDX | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| TITAN (EM4050) | | | ✓ | ✓ | ✓ | ✓ | ✓ | |
| UNIQUE | | ✓ | ✓ | ✓ | ✓ | ✓ | | |
| ZODIAC | | ✓ | ✓ | ✓ | ✓ | ✓ | | |

1) UID only 2) UID Only, read/write on request 3) Only NFC Forum Tag 2-4 4) on request depending on demand 5) only manchester f64; sequence terminator off 6) Only emulation of 4100,4102
7) r/w, enhanced security features planned 8) r/w in direct chip command mode 9) UID + r/w public area 10) Support of security level 1 11) Without crypto 12) AES only 13) Hash value only 14) UID + PAC (CSN & Facility Code), read/write on request
Elatec reserves the right to change any information or data in this document without prior notice. The distribution and the update of this document is not controlled. Elatec declines all responsibility for the use of product with any other specifications but the ones mentioned above. Any additional requirement for a specific customer application has to be validated by the customer himself at his own responsibility.